



VIEWS SHOWING HINGED PANEL MOUNTING ARRANGEMENTS

NOTES :

1. This drawing is an indication of how to lay out the meters and fuses. The spacing chosen is to allow for possible differences in future products and are based on the maximum dimensions for single phase multifunction meters in AS 1284.11 - 1995.
The layout shall apply to 2 or more meters
2. Multi-metering requires the installation of a Main Switch on the panels as per the Meter Manual Multi-metering drawings. This switch shall be positioned at the bottom corner of the meter panel.
3. The Active, Consumer Neutral and Meter Neutral links shall be mounted on the rear of the panel and shall be sealable. Meter neutral shall be a minimum of 4mm.sq.
4. A drawing shall be submitted for all multi-metering panels.
Alternative layouts shall be drawn and submitted for approval prior to commencing work.
5. For drilling details refer to typical three phase direct connect drawing, Fig. 22 sheet 3
6. Refer to fig 4 sheet 2 for wiring details.

| | | | | | | | | | | | |
|-------------------|-------------------|---------------------------|------|--------|------|---|-----------|-----------------------|-------------------|--|-------------------------------|
| PowerWater | 0 | APPROVED FOR INSTALLATION | R.W. | 4.9.09 | N.C. | DES N.COAD DRN R.WILLIAMS CKD N.COAD APPD B.KISON SCALE 1 : 10 FIG.38 HINGED METER PANEL ARRANGEMENT POLYPHASE METERS ONLY (BACKWIRED) | A4 | DRAWING NUMBER | S11-2-7-46 | | |
| | A | ISSUED FOR COMMENT | R.W. | 4.9.09 | N.C. | | | | | | ISSUED 4.9.09 |
| | NO | DESCRIPTION | DRN | DATE | APPD | | | | | | ALL DIM. IN mm |
| | AMENDMENTS | | | | | | | | | | DRAFTING STANDARD TO A.S.1100 |