



* POINT OF ATTACHMENT TO BE PROVIDED BY CONSUMER

CONDUCTOR	USE	SAG	FUSE BASE SIZE
2/C-7/1.70	1ø DOMESTIC	1.5m IN 25m	100A
4/C-7/1.70	3ø COMMERCIAL	1.5m IN 25m	100A

No.	DESCRIPTION
5	CLEARANCE POLE
4	TERMINATION - HOUSE
3	SERVICE COLUMN TOP ASSEMBLY TYPE AC T1
2	TERMINATION - POLE TYPE F.S.T.
1	SERVICE CONDUCTOR (SEE TABLE)
	DRAWING SCHEDULE

NOTES

1. FUSE CARTRIDGE TO BE DETERMINED BY THE INSPECTOR
2. CLEARANCE TO BE IN ACCORDANCE WITH DRG. S01-4-1-01
3. IN RURAL AREAS WHERE THE P.W.C. POLE IS ON THE OPPOSITE SIDE OF THE ROAD THE CONSUMER METERING POLE POINT OF ATTACHMENT SHALL BE LOCATED WITHIN ONE (1) METRE OF PROPERTY BOUNDARY
4. FOR ALL 3 PHASE SERVICES OR ANY SINGLE PHASE SERVICE GREATER THAN 30 METERS INLENGTH USE ITEM 2 IN S01-1-4-28 AS THE SERVICE CLAMP

NO	DESCRIPTION	DRN	DATE	CKD	APPD
5	NOTE 4 ADDED	A.T.	SEP'11	B.C.	S.C.
4	CONDUCTOR SIZE CHANGED	J.C.	NOV'08	A.T.	S.C.
AMENDMENTS					

PowerWater
NORTHERN TERRITORY

DES	J.HASSENEN	POWER STANDARD DRAWING	
DRN	C.KWONG	DESIGN DATA L.V. SERVICES TWISTED CONDUCTOR GENERAL ARRANGEMENT	
CKD			
APPD	...		
SCALE	N.T.S.	A3	DRAWING NUMBER S01-4-1-05
ISSUED	06/08		
ALL DIM.	IN mm	CAD PRODUCT - DO NOT AMEND MANUALLY	
DRAFTING STANDARD TO A.S.1100		AMDT	