



NOTES:

1. IF NO EXISTING SERVICE ARM, LOCATE CCO BOLT AND CROSSARM 200mm BELOW TRANSFORMER.
2. IF EXISTING SERVICE ARM, LOCATE CCO BOLT AND CROSSARM 300mm BELOW SERVICE ARM.
3. CCO TERMINATIONS ARE NOT TO BE PLACED ON TRANSFORMER POLES.
4. CCO CROSSARM TO BE ATTACHED TO PROPERTY SIDE OF SUBSTATION POLE BY PAWA STAFF.
5. 300mm MINIMUM CLEARANCE IS REQUIRED BETWEEN THE SERVICE ARM AND THE CCO BOLT AND CLAMP ATTACHMENT POINT. WHEN NON-INSULATED OR BARE CABLES AND FITTINGS ARE ATTACHED TO THE SERVICE CROSSARM OR POLE AND WORK IS TO BE PERFORMED AT OR NEAR THE CETV BOLT/CLAMP ATTACHMENT POINT, PAWA IS TO BE CONTACTED TO 'MAT UP' ALL LIVE COMPONENTS WITHIN 600mm OF THE WORK LOCATION.
6. CCO POWER SUPPLIES OR AMPLIFIERS ARE NOT TO BE ATTACHED TO AIRBREAK SWITCH, TRANSFORMER OR TEE-OFF POLES.

ELEVATION
1:40

SECTION A-A
1:40

TYPICAL SINGLE POLE SUBSTATION CCO ATTACHMENT

3	SUPERSEDED	A.T.	DEC'12	B.C.	B.C.
2	TEXT 'CETV' CHANGED TO 'CCO'. DETAIL 1 & NOTE 4 CHANGED	RGI	APR'97	MWB	FRR
1	NOTE 5 RE SAFETY CLEARANCES ADDED.	RGI	10/96	MWB	PJD
NO	DESCRIPTION	DRN	DATE	CKD	APPD
AMENDMENTS					



DES	M. BOCK	POWER STANDARD DRAWING		
DRN	R. INNES	CCO (COMMUNICATIONS CABLE OWNER) TYPICAL ATTACHMENT POSITION SINGLE POLE SUBSTATION		
CKD	M. BOCK			
APPD	P. DEWAR			
SCALE	AS SHOWN			
ISSUED	06/09/96	A3	DRAWING NUMBER	S01-02-02-26
ALL DIM.	IN mm		DRAFTING STANDARD TO A.S.1100	CAD PRODUCT - DO NOT AMEND MANUALLY