

**19.1kV SWER DISTRIBUTION TRANSFORMER
HV FUSE LINK SELECTION CHART**



TRANSFORMER SIZE	FUSE SIZE	FUSE LINK CLASS	PAWA STOCK NO	MANUFACTURERS PART NO
10kVA	1 AMP(1 off)	K(S)	NOT ON STOCK	STANGER 2 X C705-01BK37
20kVA	2 AMP(1 off)	K(S)	NOT ON STOCK	STANGER 2 X C705-02BK37
50kVA	5 AMP(1 off)	K(S)	187765	STANGER 2 X C705-06BK37

**100kVA - 22/19.1kV SWER ISOLATING TRANSFORMER
HV FUSE LINK SELECTION CHART**

	FUSE LINK SIZE	FUSE LINK CLASS	PAWA STOCK NO	MANUFACTURERS PART NO
11/22kV (PRIMARY)	10 AMP(2 off)	K(S)	187781	STANGER 2 X C705-10BK37
19.1kV (SECONDARY)	8 AMP(1 off)	K(S)	187773	STANGER 2 X C705-08BK37

NOTE:

1. FUSE LINKS TO BE USED IN CONJUNCTION WITH TYPE C-24/36kV EDO SIMILAR TO MORLYNN POWER/STANGER CAT NO XS 236, DRG NO 69148/27 - ISSUE 4.
2. K(S) = SPARKLESS TYPE.

1 NO	APPROVED FOR CONSTRUCTION.	RG1	SEP '99	MWB	FRR	 NORTHERN TERRITORY	DES M. BOCK	POWER STANDARD DRAWING				
	DESCRIPTION	DRN	DATE	CKD	APPD		DRN R. INNES	SINGLE WIRE EARTH RETURN ISOLATING / DISTRIBUTION TRANSFORMER HV FUSE SELECTION CHARTS				
AMENDMENTS								APPD F. ROBSON	SCALE NO SCALE	A3	DRAWING NUMBER S25-3-1-03	 1 AMDT
								ISSUED 20/10/97	ALL DIM. IN mm			