



**NOTES**

1. SUBSTATIONS WITH CAPACITY 750kVA AND ABOVE SHALL BE PRE FITTED WITH TWO LINKS INSTEAD OF ONE (DETAIL A).
2. REAL CONNECTIONS SHOULD BE BRIDGED ON 2000A UNIT.
3. BOTTOM CONNECTOR TO BE COVERED WITH HA TYPE COVER.
4. CONTACT COVER BENEATH HANDLES TO BE RED INSTEAD OF NORMAL YELLOW COLOUR.

**DIMENSIONS**

DIMENSIONS MAY VARY DEPENDING ON THE TYPE OF SWITCHGEAR.

**APPLICATION**

FOR USE IN PACKAGE AND KIOSK SUBSTATIONS

**MATERIAL**

BASE : MOULDED PLASTIC  
 BUSBAR : TINNED COPPER  
 VOLTAGE : 500V

**LV CABLE FLEXIBLE**

KVA	SIZE	MIN. RUNS PER PHASE
300	120	2
500	300	2
750	300	3

**STOCK CODE**

1000A	406808
2000A	406811

- 4 NOTES 2-4 ADDED. DETAIL A AMENDED.
- 3 NEW DETAIL ADDED
- 2 STCK CODES ADDED
- 1 CABLE SIZE AMENDED

NO	DESCRIPTION	DRN	DATE	CKD	APPD
	AMENDMENTS				

A.S. APR'07 R.S. B.C.  
 K.I. JAN'07 R.S. B.C.  
 K.I. SEP'06 R.S. B.C.  
 Raj Aug'06 Raj B.C.



DES C. CAMILLERI POWER STANDARD DRAWING

DRN A. SCHMID  
 CKD C. CAMILLERI  
 APPD .  
 SCALE 1 : 5

**DISCONNECTOR BASE**  
**500V. 1000 - 2000A DISCONNECTOR**

ISSUED JAN'06  
 ALL DIM. IN mm  
 DRAFTING STANDARD TO A.S.1100

**A3** DRAWING NUMBER **S02-1-4-17**

CAD PRODUCT - DO NOT AMEND MANUALLY

