

TABLE 1: 400A LV FUSE-SWITCH LINKS
REFER TO S01-01-06-08

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER
1	63	119552
2	80	247544
3	100	1313
4	125	1347
5	160	1354
6	200	1370
7	250	1388
8	315	1420
9	400	1438

TABLE 2: 800A LV FUSE-SWITCH LINKS
REFER TO S01-01-06-08

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER
10	315	119552
11	355	247544
12	400	1313
13	450	1347
14	500	1354
15	630	1370
16	710	1388
17	800	1420

TABLE 4: EDO FUSE LINKS
REFER TO S01-01-06-05

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER
42	5	187765
43	8	187773
44	10	187781
45	16	255810
46	20	255828
47	25	255836
48	31.5	255844
49	40	255851
50	50	255869
51	63	255877
52	80	255885
53	100	283226
54	200	407373

TABLE 6: LV SWITCH-FUSE DISCONNECTOR (STRIPLE) FUSE LINKS
REFER TO S02-01-04-10

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER	SIZE
67	63	286211	00
68	80	26229	00
69	100	286237	00
70	125	286245	00
71	160	205088	00
72	35	157974	1
73	63	10058	1
74	100	10066	1
75	125	158162	1
76	160	11064	1
77	200	9712	1
78	250	11072	1
79	315	9761	2
80	355	9720	2
81	400	9738	2
82	500	9746	3
83	600	9753	3

TABLE 3: RMU DIN FUSE LINKS
REFER TO S01-01-06-05

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER	VOLTAGE (kV)	FUSE LENGTH (mm)	FUSE TYPE	RMU TYPE
18	40	415329	11	292	FULL RANGE	HOLEC MD4
19	63	415330	11	292	FULL RANGE	HOLEC MD4
20	80	415331	11	292	FULL RANGE	HOLEC MD4
21	63	414969	11	292	BACK UP	DRIESCHER/SM6
22	80	414970	11	292	BACK UP	DRIESCHER/SM6
23	100	415332	11	292	BACK UP	DRIESCHER/SM6
24	125	415457	11	292	BACK UP	DRIESCHER/SM6
25	100	503431	11	442	BACK UP	RM6/SM6
26	31.5	500513	11/22	292	BACK UP	DRIESCHER
27	40	414971	11/22	292	BACK UP	DRIESCHER
28	50	414972	11/22	292	BACK UP	DRIESCHER
29	20	500858	11/22	442	BACK UP	RM6/SM6
30	31.5	500859	11/22	442	BACK UP	RM6/SM6
37	40	500860	11/22	442	BACK UP	RM6/SM6
38	50	500861	11/22	442	BACK UP	RM6/SM6
39	63	503698	11/22	442	BACK UP	RM6/SM6
40	80	414974	11/22	442	BACK UP	RM6/SM6
41	125	414975	11/22	442	BACK UP	RM6/SM6

TABLE 5: LV FERRULE SERVICE FUSES
REFER TO S01-01-04-12 & S01-01-04-49

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER	SIZE
55	6	9852	51x14
56	10	9860	51x14
57	20	401053	51x14
58	40	10207	51x14
59	50	10231	51x14
60	10	300376	57x22
61	20	500828	57x22
62	30	500725	57x22
63	45	501464	57x22
64	63	10322	57x22
65	80	10314	57x22
66	100	216028	57x22

TABLE 7: LV SWITCH-FUSE DISCONNECTOR (STRIPLE) SOLID LINKS
REFER TO S02-01-04-10

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER	SIZE
84	160	286211	00
85	250	26229	1
86	1250	286237	3

TABLE 8: MCCB'S ONLY
REFER TO S02-02-08-03

ITEM REF.	CURRENT RATING (A)	ITEM NUMBER
87	400	503899
88	800	503885
89	1600	503902
90	2000	502486

NO	DESCRIPTION	DRN	DATE	CKD	APPD
4	UPDATED ALL TABLES & ITEM NUMBERS, UPDATED TITLE	A.N.	JUL '21	A.N.	B.C.
3	TITLEBLOCK & DRAWING NUMBER FORMATTED	K.T.	APR '19	C.C.	C.C.
2	HV DIN FUSE RANGE EXTENDED	A.T.	APR '14	B.C.	B.C.
1	TABLES CHANGED	A.C.S	APR '13	A.T.	B.C.
0	ISSUED	J.C.	MAR '08	A.T.	S.C.
AMENDMENTS					



DES	A. TAYLOR	POWER STANDARD DRAWING	
DRN	J. COPPINS	DESIGN DATA HV AND LV FUSES ITEM NUMBERS	
CKD	A. TAYLOR		
APPD	S. C.		
SCALE	N. T. S.		
ISSUED	MAR '08	A3	DRAWING NUMBER S02-04-02-11
ALL DIM.	IN mm		
DRAFTING STANDARD TO A.S.1100		CAD PRODUCT - DO NOT AMEND MANUALLY	

